

# POWER MIXER USB AMPLIFIER

\_MODEL KU-1000B

USB & SD PLAYER / FM RADIO



**MUSIC**  
Professional Natural Music Sound.



## Specification

TYPE ..... POWER MIXER TRANSISTOR BUILT-IN USB PLAYER / SD PLAYER / FM

INPUT ..... 5 MIC IMPEDANCE 600 Ω (PHONE JACK)

..... AUX.1 IMPEDANCE 47k Ω (RCA JACK)

..... AUX.2 / USB / SD / FM IMPEDANCE 47k Ω (RCA JACK)

..... \*\*AUTO MUTE AUX.1-2 WHEN MIC.5 USED

INPUT CONTROL ..... VOLUME PER CHANNEL

INPUT TONE CONTROL ..... LOW - HIGH +/-16 dB PER CHANNEL

MASTER CONTROL ..... MASTER VOLUME CONTROL

MASTER TONE CONTROL ..... LOW - MIDDLE - HIGH +/-16 dB

MASTER OPTION ..... MAIN IN (PHONE JACK), MAIN OUT (PHONE JACK)

..... PRE OUT (PHONE JACK), RECORD OUT (PHONE JACK)

..... ECHO IN (PHONE JACK), OUT to ECHO (PHONE JACK)

INPUT SENSITIVITY ..... 1 V.RMS AT 1 kHz AT 8 Ω

SIGNAL-TO-NOISE ..... 100 dB BELOW MAX LEVEL

FREQUENCY RESPONSE ..... 50 Hz - 20 kHz AT +/-3 dB

THD+NOISE ..... LESS THAN 0.02% (20 Hz - 40 kHz AT +10 dB)

Model.

**KU-1000B**

OPTION

DELAY INPUT WHILE TURN ON

BUILT-IN COOLING FAN, AC OUTLET

POWER DISPLAY (LINE LED)

POWER ON LED

POWER REQUIREMENTS

AC~220 V 50/60 Hz

OUTPUT

SPEAKER 2 - 4 Ω, 8 - 16 Ω

LINE MATCHING 70V, 100V

POWER OUTPUT

MODEL	POWER	DIMENSIONS (W x H x D)	WEIGHT
KU-550B	550 W.RMS	483 mm x 140 mm x 500(460) mm	32 kg
KU-750B	750 W.RMS	483 mm x 140 mm x 500(460) mm	34 kg
KU-1000B	1000 W.RMS	483 mm x 140 mm x 500(460) mm	38 kg
KU-1200B	1200 W.RMS	483 mm x 140 mm x 500(460) mm	39 kg